# **Specifications**

### TZY31 InstaShare Button Solution

Color Wi-Fi Standard Interface Wi-Fi band

#### TWY31 InstaShare Button



| I.RM03  | series | (with U | SB Тур |
|---------|--------|---------|--------|
| 2.RP02, | REOI,  | RM02K,  | RM02   |

Compatibility

| I.RM03 series (with USB Type-C)     |
|-------------------------------------|
| 2.RP02, RE01, RM02K, RM02S, CP01K,  |
| CS01, SL02K series, and VC01A (with |
| USB Type-C to USB Type-A adapter)   |

| Color                            | Silver   |  |  |
|----------------------------------|--|--|--|
| Wireless Transmission Frame Rate | Up to 60 fps depending on environment(1080P60/4K30P)   |  |  |
| TX Button Input resolution       | Up to 4K30P  |  |  |
| Audio Rate                       | Stereo, Radio quality 16bits 48KHz   |  |  |
| Wi-Fi Standard                   | IEEE 802. I Iac 5GHz, 2T2R MIMO  |  |  |
| Authentication protocol          | Wi-Fi Standard   |  |  |
| Wireless Security (Encryption)   | WPA2/3 Personal/WPA2 Enterprise Support AES-256  |  |  |
| Wireless Coverage Reach          | Max. 15 m (Between Button and IFP)   |  |  |
| Cable                            | USB Type C   |  |  |
| Power Supply                     | DC 5V±10%, Minimum 0.9A  |  |  |
| Power Consumption                | Max 4.5W Full Loading  |  |  |
| Dimension (WxHxD)                | 67mm x 67mm x23.2mm  |  |  |
| Temperature range                | Operating: 0°C to +40°C (+32°F to +104°F)<br>Storage: -10°C to +60°C (+14°F to +140°F)           |  |  |
| Humidity range                   | Operating: 10% to 80% relative humidity<br>Storage: 5% to 90% relative humidity (non-condensing) |  |  |

TDY31 BenQ Wireless USB Dongle

|  |  | _ |
|--|--|---|
|  |  |   |



Compatibility

series, and VC01A

| MU-MIMO                 |
|-------------------------|
| Wi-Fi Performance       |
| External Antenna        |
| Supported OS            |
| Wireless Coverage Reach |
| Security                |
| Power Supply            |
| Dimension L*H*W         |
| Net Weight              |
| Temperature range       |
| Humidity range          |

| Black                              |
|------------------------------------|
| 802.11 a/b/g/n/ac                  |
| USB 3.0                            |
| Dual Band 2.4GHz / 5GHz            |
| Yes                                |
| 2.4 GHz Band: up to 400 Mbps       |
| 5 GHz Band: up to 867 Mbps         |
| 2                                  |
| Android                            |
| Max. 15 m (Between Dongle and IFP) |
| WPA-PSK/WPA2-PSK WPA/WPA2/WEP      |
| DC 5V, 0.9A (Maximum)              |
| 37 x 41 x 12 mm                    |
| 0.055kg                            |
| Operation : 0°C~40°C               |
| Storage : -40°C~70°C               |
| Operation: 10%~90%                 |
| Storage: 5%~90%                    |
|                                    |

#### TCY31 BenQ InstaShare Dock

RM03, RP02, RE01, RM02K, RM02S, CP01K, CS01, SL02K, ST02, ST02S, IL01, BH01, BH01T, BH01N, BH01D



| Weight (Net)                         |
|--------------------------------------|
| Dimension L*H*W                      |
| "InstaShare Button Loading quantity" |
| Product material                     |

Color

| Black                                     |
|---|
| 420 g                                     |
| 150 x 85 x 106 mm                         |
| 4 pcs                                     |
| PC+ABS & Aluminum alloy 6063 & Silica gel |

Headquarters BenQ Corporation 16 Jihu Road, Neihu, Taipei 114, Taiwan Tel : +886-2-2727-8899 Fax : +886-2-2656-2438 Asia Pacific BenQ Asia Pacific Corp. 12 Jihu Road, Neihu, Taipei 114, Taiwan Tel : +886-2-2727-8899 Fax : +886-2-2656-2438 China BenQ (IT) Co., Ltd. 181 Zhuyuan Road, Suzhou New District, Suzhou, China Tel : +86-512-6807-8800 Fax : +86-512-6809-7010

North America BenQ America Corp. Europe BenQ Europe B.V. 3200 Park Center Drive, Suite 150 Costa Mesa, CA 92626 U.S.A Meerenakkerweg I-17, 5652 AR Eindhoven, The Netherlands Tel : +31(0) 88-888-9200 U.S.A Tel : +1-714-559-4900 Fax : +1-714-557-0200 Fax : +31(0) 88-888-9299

Latin and Central America BenQ Latin America Corp. 8200 N.W. 33 Street, Suite 301 Miami, FL 33122 U.S.A. Tel: +1-305-4211200 Fax: +1-305-4211201

© 2022 BenQ Corp. Specification may vary by reigon, please visit your local stores for details. Actual product's features and specifications are subject to change without notice. This material may include corporate names and trademarks of third parties which are the properties of the third partiesrespectively Doc: PDP\_TZY31/TWY31/TDY31/TCY31\_IFP\_EN\_202202



# **One-click wireless screen sharing**

Get ready to welcome a new generation of meetings where you're free to move around and share content without limits. Whether it's to share details with the room or start video conferencing on the large screen, the InstaShare Button Solution eliminates the fuss of passing around cables so everyone can focus on what's important-your ideas.



## Seamless content sharing for all notebooks

Wirelessly share content with everyone in the meeting no matter what notebook you're using. The InstaShare Button Solution is compatible with Windows, macOS, and Chrome OS laptops.

### Get everyone involved

Enhance productivity with a side-by-side view of everyone's contributions. The InstaShare Button Solution works with InstaShare 2, a wireless screen sharing software that lets up to 9 devices cast content simultaneously on your BenQ display.





# Perfectly set up video calls with your display

Ensure everyone in the meeting can be seen and powerful built-in speakers when you launch videocalls from your notebook.

\*Available starting Q2 2022

**Convenient connectivity** 

content with a single click.

The USB Type-C connector enables a one-cable

plug-and-play solution that works seamlessly with

Windows notebooks, MacBooks, and Chromebooks.

Just plug the InstaShare Button in and start sharing


## Complete control with touchback

Enhance collaboration with seamless content sharing. The InstaShare Button lets you cast personal device screens onto the BenQ display to let all meeting attendees see. With touchback, users can also control shared devices right from the display.



#### Share content your way

Easily switch between casting your entire screen or customizing the content you show. With the InstaShare Button Solution, you can opt to share photos, videos, audio, or your camera feed for flexible discussions without interruptions.



heard clearly, whether they're in the room or joining remotely. Employ the display's external camera and









# Industry-leading connection quality

Enjoy smooth meetings without disruptions. The InstaShare Button Solution features industry-leading connection quality to ensure stable screen sharing no matter where you sit in the room.